

OPERATION CONFIRMED COMPACT FLASH CARD LIST FOR FOSTEX MODEL MR-8 (with V1.20 or later software)

9th Issue (September 1, 2005)

1. OPERATION-CONFIRMED COMPACTFLASH CARDS

Important Notice

The listed CF cards were confirmed to operate properly with model MR-8 through our lab tests on the cards Fostex optionally obtained from the market. However, this does not mean all the cards of the same manufacturer and of the same model name / number / same capacity always work properly due to different internal configuration depending on manufacturing time and place. This should not be taken as an evaluation of general quality of each CF card.

Manufacturers (Type/series)	128MB	256MB	512MB	1GB	2GB	Card Info	Firm. Rev.
Hagiwara Sys-Com (Z-Pro series)	-	-	-	C	-	TOSHIBA THNCF1G02CA	3.00
Hagiwara Sys-Com (Z-Pro series)	C	C	C	-	-	TOSHIBA THNCFxxxMCA	3.00
Hagiwara Sys-Com (Z series)	C	C	C	-	-	TOSHIBA THNCFxxxMBA	2.20
Hagiwara Sys-Com (V series)	C	C	C	-	-	TOSHIBA THNCFxxxMMA	3.10
Hagiwara Sys-Com (V series)	-	-	-	C	-	TOSHIBA THNCF1G02MA	3.10
DELKIN DEVICES eFilm PRO	C	C	C	-	-	CFXXX	30/06/03
DELKIN DEVICES eFilm PRO	-	-	-	C	-	ATA01G	30/06/03
DELKIN DEVICES eFilm CF	-	-	-	C	-	TOSHIBA THNCF1G02MA	3.10
RENESAS HB28BxxxC8C series	C	C	-	-	-	Hitachi XXM2.3.0	Rev 3.00
SimpleTech	C	C	C	-	-	STI Flash 6.2.0	Rev 6.2.0
SimpleTech ProX	C	C	C	-	-	STI Flash 1T	CFCA207C
Kingston CF Memory Card	-	-	-	C	-	TOSHIBA THNCF1G02MA	3.10
Kingston CF Memory Card	-	-	C	-	-	Hitachi XX.V.3.3.0.0	Rev 0.00
Ritek RiDATA CF Card 52X/PRO	-	-	C	C	-	CF-ATA	1.1
Lexar High Speed Professional 40x	-	-	C	C	-	LEXAR ATA FLASH	V1.00/1.02
Transcend CF 45x	C	C	C	-	-	Transcend xxxM	1.1
Transcend CF 45x	-	-	-	C	-	Transcend 1G02	1.1
Transcend CF 45x	-	-	-	-	C	Transcend 2G04	1.1
TOSHIBA CF Card	C	C	C	-	-	TOSHIBA THNCFxxxMBA	2.20
TOSHIBA CF Card	C	C	C	C	-	TOSHIBA THNCFxxxMMA	V3.10
TOSHIBA CF Card *	C	C	C	C	-	TOSHIBA THNCFxxxMMG	V3.10

C: Confirmed, -: Not checked, x: Does not work

Depending on the difference of hardware configuration, the same manufacturer's and same model number of CF card with different capacity may not work properly.

Card Info can be confirmed on the MR-8 display by pressing "STOP" and "MENU" keys simultaneously and then accessing Service -> Card Info.

We only assure the operation of the above CF cards with the corresponding Card Info.

In order to correctly recognize the above CF card, the MR-8 software must be updated to **V1.20** onwards.

* Update the software to **V1.21** when using the TOSHIBA CF Card at EXTENDED mode. Otherwise, there is a case that the error message (e.g. Error 09, Error 12) is displayed.

The following manufacturers/types are found unsuitable for use in MR-8 through our lab tests. However, this should not be taken as an evaluation of general quality of each CF card.

- * Green House
- * SanDisk
- * SanDisk ultra (CF Info: SDCFH-xxx)

2. RECORDING TIME CHART

APPROX. MINUTES

CAPACITY	MONO	2TR	4TR	6TR	8TR
128MB	24 (48)	12 (24)	6 (12)	4 (8)	3 (6)
256MB	48(96)	24(48)	12(24)	8(16)	6(12)
512MB	96(193)	48(96)	24(48)	16(32)	12(24)
1GB	188 (377)	94 (188)	47 (94)	31 (62)	23 (47)
2GB	377 (755)	188 (377)	94 (188)	62 (125)	47 (94)

*Minutes in parenthesis: extended mode